

## OHL Installation Instructions



1. Unpack OHL Fixture and remove blue protective tape from the lens by peeling off.



5. Make all necessary termination of conductors and re-secure end plates to the fixture.



2. Remove the two screws that secure the end plate assembly onto the fixture



3. Pull out/extend conductors from the junction tray.



6. When installing multiple fixtures, they can be daisy-chained one to the next by using flex or rigid greenfield conduit.



4. Secure the OHL fixture to the lid of the box using self-tapping screws.



7. Install end plugs into fixture(s) as needed.



5. Mount applicable conduit hardware onto the fixtures end plate.



8. Energize light circuit and check for proper operation of all newly installed LED fixtures.

For more information please contact

**SCHOTT Gemtron**  
Food Display Division  
2840 Nebo Road.  
Madisonville, KY 42431

Toll Free 800.326.2717  
Phone 270.821.2864  
Fax 270.326.3624  
[www.gemtrondoors.com](http://www.gemtrondoors.com)

**SCHOTT**  
Gemtron

Rev 01/10 MM50